



## **AS2015**

*2000 series loop powered sounder*

### **User friendly**

---

This high-output loop-powered sounder is a powerful addition to the 2000 series sensor products. Absolute control and flexibility is obtained when used with the FP1200 and FP2000 range of firepanels. The low current consumption makes it possible to install many sounders on the loop, while maintaining system integrity with other 2000 series sensors and io modules.

The sounders are available in red or white.

### **Installer friendly**

---

Installation is quick and easy. The two-wire loop is wired in and then out to the next device. The address is set on an eight-way DIP switch. No other settings are required!

### **Flexible programming**

---

The FP1200 and FP2000 fire panel's powerful logic programming makes it easy to individually program the sounders. A choice of three tones can be selected individually for each sounder. The sounders can be set to follow warning or evacuation, or can be set to any of the three tones at will using logic.

### **Integral isolator**

---

The integral isolator of the AS2015 will sense and isolate short circuit faults. The sounder will still continue to receive power and thus still functions in the event of a single short circuit.



### **Standard Features**

---

- **Loop powered**
- **Low current**
- **High output**
- **Built in isolators**
- **3 tones**
- **FP1200 / 2000 fire panel operation**



# AS2015

2000 series loop powered sounder

## Specifications

<b>Operating voltage</b>	17-39 VDC
<b>Supply current</b>	
not activated	240 $\mu$ A
activated	3mA
<b>Sound output @ 1 meter</b>	100 dB(A)
<b>Continuous tone</b>	990 Hz
<b>Intermittent tone</b>	990 Hz, On Off @ 1 Hz
<b>Two tone</b>	990 Hz / 650 Hz @ 1 Hz

## Ordering Information

Part No.	Description
AS2015	2000 series loop powered sounder
AS2015W	2000 series loop powered sounder - white



**GE Interlogix**

<http://www.GE-interlogix.com>